

Data sheet

CPU 313SC DPM (313-6CF23)

Technical data

Order no.	313-6CF23
Туре	CPU 313SC DPM
General information	
Note	
Features	Powered by SPEED7 Work memory [KB]: 2561.024 Onboard: 16x DI / 16x DO / 3x Counter / 3x PWM Interface [RJ45]: Ethernet PG/OP communication Interface [2x RS485]: MPI, PROFIBUS master/slave, PtP: ASCII, STX/ETX, 3964 (R), USS master, Modbus master/slave Including front connector SD/MMC card slot with locking, up to 32 modules stackable, programmable with WinPLC7, SIMATIC Manager and TIA Portal
SPEED-Bus	-
Technical data power supply	
Power supply (rated value)	DC 24 V
Power supply (permitted range)	DC 20.428.8 V
Reverse polarity protection	yes
Current consumption (no-load operation)	200 mA
Current consumption (rated value)	900 mA
Inrush current	11 A
2 _t	0.7 A ² s
Max. current drain at backplane bus	3 A
Max. current drain load supply	-
Power loss	14 W
Technical data digital inputs	
Number of inputs	16
Cable length, shielded	1000 m
Cable length, unshielded	600 m
Rated load voltage	DC 24 V
Reverse polarity protection of rated load voltage	yes
Current consumption from load voltage L+ (without load)	70 mA
Rated value	DC 24 V
Input voltage for signal "0"	DC 05 V
Input voltage for signal "1"	DC 1528.8 V
Input voltage hysteresis	-
Signal logic input	Sinking input
Frequency range	-
Input resistance	-
Input current for signal "1"	6 mA
Connection of Two-Wire-BEROs possible	yes
Max. permissible BERO quiescent current	1.5 mA
Input delay of "0" to "1"	0.1 / 0.35 ms
Input delay of "1" to "0"	0.1 / 0.35 ms



Number of simultaneously utilizable inputs horizontal configuration	16
Number of simultaneously utilizable inputs vertical configuration	16
Input characteristic curve	IEC 61131-2, type 1
Initial data size	2 Byte
Technical data digital outputs	
Number of outputs	16
Cable length, shielded	1000 m
Cable length, unshielded	600 m
Rated load voltage	DC 24 V
Reverse polarity protection of rated load voltage	-
Current consumption from load voltage L+ (without load)	100 mA
Total current per group, horizontal configuration, 40°C	3 A
Total current per group, horizontal configuration, 60°C	2 A
Total current per group, vertical configuration	2 A
Output voltage signal "1" at min. current	L+ (-0.8 V)
Output voltage signal "1" at max. current	L+ (-0.8 V)
Output current at signal "1", rated value	0.5 A
Signal logic output	Sourcing output
Output current, permitted range to 40°C	5 mA to 0.6 A
Output current, permitted range to 60°C	5 mA to 0.6 A
Output current at signal "0" max. (residual current)	0.5 mA
Output delay of "0" to "1"	100 µs
Output delay of "1" to "0"	100 µs
Minimum load current	-
Lamp load	5 W
Parallel switching of outputs for redundant control of a load	possible
Parallel switching of outputs for increased power	not possible
Actuation of digital input	yes
Switching frequency with resistive load	max. 2.5 kHz
Switching frequency with inductive load	max. 0.5 Hz
Switching frequency on lamp load	max. 2.5 kHz
Internal limitation of inductive shut-off voltage	L+ (-52 V)
Short-circuit protection of output	yes, electronic
Trigger level	1 A
Number of operating cycle of relay outputs	-
Switching capacity of contacts	-
Output data size	2 Byte
Technical data analog inputs	
Number of inputs	-
Cable length, shielded	-
Rated load voltage	-
Reverse polarity protection of rated load voltage	-
Current consumption from load voltage L+ (without load)	-
Voltage inputs	-
Min. input resistance (voltage range)	-
Input voltage ranges	-
Operational limit of voltage ranges	-

Basic error limit voltage ranges with SFU - Destruction limit voltage ranges with SFU - Oestruction limit voltage ranges with SFU - Oestruction limit voltage ranges Max. Input resistance (current range) - Input current ranges - Operational limit of current ranges - Operational limit of current ranges with SFU - Basic error limit current ranges with SFU - Oestruction limit current ranges with SFU - Destruction limit current ranges with SFU - Destruction limit current ranges with SFU - Operational limit of current ranges with SFU - Operational limit or current inputs (electrical current) - Operational limit or desistor ranges - Operational limit or fesistor ranges - Operational limit or sestor ranges with SFU - Destruction limit resistor ranges - Operational limit of resistor ranges with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Destruction limit resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges with SFU - Basic error limit thermoresistor ranges with SFU - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer ranges with SFU - Destruction limit resistance thermometer ranges with SFU - Destruction limit of thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU -		
Basic error limit voltage ranges with SFU Current inputs Max. input resistance (current range) Input current ranges Operational limit of current ranges Operational limit of current ranges Basic error limit current ranges with SFU Destruction limit current ranges with SFU Destruction limit current ranges with SFU Destruction limit current inputs (voltage) Resistance inputs Resistance ranges Operational limit of resistor ranges with SFU Destruction limit current ranges with SFU Destruction limit current inputs (voltage) Resistance inputs Resistance ranges Operational limit of resistor ranges with SFU Destruction limit of resistor ranges Operational limit of resistor ranges with SFU Basic error limit with SFU Destruction limit resistance inputs Resistance thermometer inputs Resistance thermometer ranges Operational limit of remoccupie ranges with SFU Destruction limit resistance thermometer ranges Operational limit of remoccupie ranges Destruction limit resistance thermometer ranges Operational limit of thermoccupie ranges Operational limit of thermoccupie ranges with SFU Destruction limit resistance thermometer ranges Operational limit of thermoccupie ranges Destruction limit resistance thermometer ranges Operational limit of thermoccupie ranges Operational limi	Operational limit of voltage ranges with SFU	-
Destruction limit voltage		-
Current inputs		-
Max. input resistance (current ranges -	Destruction limit voltage	-
Input current ranges - Operational limit of current ranges - Operational limit of current ranges with SFU - Basic error limit current ranges with SFU - Destruction limit current ranges with SFU - Destruction limit current inputs (voltage) - Resistance inputs - Resistance inputs - Resistance inputs - Resistance inputs - Resistance limit of resistor ranges - Operational limit of resistor ranges with SFU - Basic error limit with SFU - Destruction limit current inputs (voltage) - Resistance thermometer inputs - Basic error limit with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistor ranges with SFU - Basic error limit with SFU - Destruction limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges - Destruction limit resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple inputs - Thermocouple inputs - Thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Destruction limit the	Current inputs	-
Operational limit of current ranges Operational limit of current ranges Basic error limit current ranges with SFU Operational limit or furth current ranges with SFU Operational limit current inputs (electrical current) Operational limit current inputs (voltage) Resistance ranges Operational limit of resistor ranges Operational limit of resistor ranges with SFU Operational limit of resistance inputs Resistance thermometer ranges Operational limit of resistance thermometer ranges with SFU Operational limit of thermoresistor ranges with SFU Operational limit of thermocouple ranges Operational limit of thermocouple ranges with SFU Operational limit of thermocouple ranges with SFU Oper	Max. input resistance (current range)	-
Departional limit of current ranges with SFU - Basic error limit current ranges with SFU - Destruction limit current inputs (electrical current) - Destruction limit current inputs (electrical current) - Destruction limit current inputs (voltage) - Resistance inputs - Resistance ranges - Departional limit of resistor ranges - Departional limit of resistor ranges - Departional limit of resistor ranges with SFU - Destruction limit resistance inputs - Resistance ranges - Departional limit of resistor ranges with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer ranges - Departional limit of resistance inputs - Resistance thermometer ranges - Departional limit of resistance thermometer ranges with SFU - Destruction limit thermoresistor ranges - Departicution limit resistance thermometer rinputs - Destruction limit resistance thermometer ranges with SFU - Destruction limit thermocouple ranges - Departional limit of thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple ranges - Departional limit of thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple ranges - Departional limit of thermocouple ranges with SFU - Destruction limit thermocouple ran	Input current ranges	-
Basic error limit current ranges with SFU - Destruction limit current inputs (electrical current) - Destruction limit current inputs (voltage) - Resistance limit current inputs (voltage) - Resistance ranges - Departuction limit current inputs (voltage) - Resistance ranges - Departuctional limit of resistor ranges - Departuctional limit of resistor ranges - Departuctional limit of resistor ranges with SFU - Departuctional limit of resistor ranges with SFU - Destruction limit resistance inputs - Resistance thermometer ranges - Destruction limit resistance inputs - Resistance thermometer ranges - Departuctional limit of resistance thermometer ranges - Departuctional limit of resistance thermometer ranges - Departuctional limit of resistance thermometer ranges - Destruction limit resistance thermometer ranges - Destruction limit resistance thermometer ranges - Destruction limit temperasistor ranges with SFU - Destruction limit temperasistor ranges with SFU - Destruction limit temperasitor ranges with SFU - Destruction limit temperasitor ranges with SFU - Destruction limit to thermocouple ranges - Departuction limit to thermocouple ranges - Departuction limit to thermocouple ranges - Departuction limit of thermocouple ranges - Departuction limit to thermocouple ranges - Departuction limit thermocouple ranges - Departure - Departu	Operational limit of current ranges	-
Radical error limit current ranges with SFU - Destruction limit current inputs (electrical current) - Destruction limit current inputs (voltage) - Resistance inputs - Resistance ranges - Operational limit of resistor ranges - Operational limit of resistor ranges with SFU - Basic error limit with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistor anges with SFU - Destruction limit resistance inputs - Resistance thermometer ranges - Operational limit of resistance thermometer inputs - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Destruction limit resistance thermometer inputs - Destruction limit fresistance thermometer inputs - Destruction limit fresistance thermometer inputs - Destruction limit thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit demonal limit of thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit demonal limit of thermocouple ranges	Operational limit of current ranges with SFU	-
Destruction limit current inputs (voltage) Resistance inputs Resistance inputs Resistance ranges Operational limit of resistor ranges Operational limit of resistor ranges with SFU Basic error limit with SFU Destruction limit resistance inputs Resistance thermometer inputs Resistance thermometer inputs Resistance thermometer inputs Resistance thermometer ranges Operational limit of resistore store store with SFU Destruction limit resistance thermometer ranges Operational limit of resistance thermometer ranges Operational limit of resistance thermometer ranges Operational limit of resistance thermometer ranges with SFU Basic error limit thermoresistor ranges with SFU Destruction limit resistance thermometer inputs Thermocouple inputs Operational limit of thermocouple ranges Operational limit of thermocouple ranges Poperational limit of thermocouple ranges Operational limit of thermocouple ranges Poperational limit for thermocouple ranges with SFU Basic error limit thermocouple ranges with SFU Destruction limit thermocouple ranges with SFU Basic error limit thermocouple ranges with SFU Basic	Basic error limit current ranges	•
Destruction limit current inputs (voltage) - Resistance inputs - Resistance ranges - COperational limit of resistor ranges - COperational limit of resistor ranges with SFU - COPERATION CONTRACT OF C	Radical error limit current ranges with SFU	-
Resistance inputs	Destruction limit current inputs (electrical current)	-
Resistance ranges - Operational limit of resistor ranges with SFU - Seasic error limit esistance inputs - Seasistance thermometer ranges - Seasistance thermometer ranges - Seasicance limit of resistance thermometer ranges - Seasicance limit of resistance thermometer ranges - Seasic error limit thermoresistor ranges with SFU - Seasic error limit of thermocouple ranges - Seasic error limit of thermocouple ranges - Seasic error limit of thermocouple ranges - Seasic error limit thermocouple ranges - Seasic error limit thermocouple ranges - Seasic error limit thermocouple ranges with SFU - Seasic error limit theresistance thermometer limit thermocouple ranges with SFU - Seasic	Destruction limit current inputs (voltage)	-
Operational limit of resistor ranges - Operational limit of resistor ranges with SFU - Basic error limit error limit with SFU	Resistance inputs	-
Operational limit of resistor ranges with SFU - Basic error limit with SFU - Capability of the programmable temperature compensation internal temperature compensation internal temperature compensation internal temperature compensation internal temperature compensation in limit of temperature measurement intilitied data size Tochnical data analog outputs - Capable for Manage of Capable (Manage) - Capable (Agrace) - Capab	Resistance ranges	-
Basic error limit with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Destruction limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Destruction limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Dest	Operational limit of resistor ranges	-
Basic error limit with SFU - Destruction limit resistance inputs - Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of thermocouple ranges with SFU - Basic error limit of ther	Operational limit of resistor ranges with SFU	-
Destruction limit resistance inputs Resistance thermometer inputs Resistance thermometer ranges Operational limit of resistance thermometer ranges Operational limit of resistance thermometer ranges Operational limit of resistance thermometer ranges with SFU Basic error limit thermoresistor ranges Basic error limit thermoresistor ranges with SFU Destruction limit resistance thermometer inputs Thermocouple inputs Thermocouple ranges Operational limit of thermocouple ranges Destruction limit thermocouple ranges Operational limit of thermocouple ranges Operational lim	Basic error limit	-
Resistance thermometer inputs - Resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges with SFU - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - External temperature compensation - External temperature compensation - Technical unit of temperature measurement - Resolution in bit - Resolution in bit - Resolution in bit - Chean audit of temperature measurement - Resolution in bit - Chean audit of temperature measurement - Resolution in bit - Chean audit of temperature measurement - Chean audit of temperature measurement - Chean audit of temperature compensation - Technical data analog outputs Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs Cable length, shielded - Rated load voltage -	Basic error limit with SFU	-
Resistance thermometer ranges - Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs Cable length, shielded - Rated load voltage -	Destruction limit resistance inputs	-
Operational limit of resistance thermometer ranges - Operational limit of resistance thermometer ranges with SFU - Basic error limit thermoresistor ranges - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Resistance thermometer inputs	-
Operational limit of resistance thermometer ranges with SFU Basic error limit thermoresistor ranges Basic error limit thermoresistor ranges with SFU Destruction limit resistance thermometer inputs Thermocouple inputs Thermocouple ranges Operational limit of thermocouple ranges Basic error limit thermocouple ranges Basic error limit thermocouple ranges with SFU Destruction limit thermocouple inputs Programmable temperature compensation External temperature compensation Internal temperature compensation Technical unit of temperature measurement Resolution in bit Measurement principle Basic conversion time Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs Cable length, shielded Rated load voltage	Resistance thermometer ranges	-
Basic error limit thermoresistor ranges - Basic error limit thermoresistor ranges with SFU - Destruction limit resistance thermometer inputs - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Operational limit of resistance thermometer ranges	-
Basic error limit thermoresistor ranges with SFU Destruction limit resistance thermometer inputs Thermocouple inputs Thermocouple ranges Operational limit of thermocouple ranges Basic error limit thermocouple ranges with SFU Destruction limit thermocouple ranges with SFU Destruction limit thermocouple inputs Programmable temperature compensation External temperature compensation External temperature compensation Technical unit of temperature measurement Resolution in bit Measurement principle Basic conversion time Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs Cable length, shielded Rated load voltage -	Operational limit of resistance thermometer ranges with SFU	-
Destruction limit resistance thermometer inputs	Basic error limit thermoresistor ranges	-
Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage	Basic error limit thermoresistor ranges with SFU	-
Thermocouple ranges - Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Destruction limit resistance thermometer inputs	-
Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Retained Note of the process	Thermocouple inputs	-
Operational limit of thermocouple ranges with SFU Basic error limit thermocouple ranges Basic error limit thermocouple ranges with SFU Destruction limit thermocouple inputs Programmable temperature compensation External temperature compensation Internal temperature compensation Technical unit of temperature measurement Resolution in bit Measurement principle Basic conversion time Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs Cable length, shielded Retain SFU	Thermocouple ranges	-
Basic error limit thermocouple ranges	Operational limit of thermocouple ranges	-
Basic error limit thermocouple ranges with SFU Destruction limit thermocouple inputs Programmable temperature compensation External temperature compensation Internal temperature compensation Technical unit of temperature measurement Resolution in bit Measurement principle Basic conversion time Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs Cable length, shielded Retain an analog outputs Retain an analog outputs Cable length, shielded Retain an analog outputs Retain analog outputs Cable length, shielded	Operational limit of thermocouple ranges with SFU	
Destruction limit thermocouple inputs Programmable temperature compensation External temperature compensation Internal temperature compensation Internal temperature compensation Technical unit of temperature measurement Resolution in bit - Resolution in bit - Measurement principle Basic conversion time - Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage	Basic error limit thermocouple ranges	
Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Basic error limit thermocouple ranges with SFU	
External temperature compensation - Internal temperature compensation - Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Destruction limit thermocouple inputs	
Internal temperature compensation - Cechnical unit of temperature measurement - Cessolution in bit - Cessolution in bit - Cessolution time - Cessolution time - Cessolution for frequency - Cessolutio	Programmable temperature compensation	
Technical unit of temperature measurement - Resolution in bit - Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	External temperature compensation	
Resolution in bit Measurement principle Basic conversion time Noise suppression for frequency Initial data size Technical data analog outputs Number of outputs Cable length, shielded Rated load voltage - - - - - - - - - - - - -	Internal temperature compensation	
Measurement principle - Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Technical unit of temperature measurement	-
Basic conversion time - Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Resolution in bit	-
Noise suppression for frequency - Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Measurement principle	-
Initial data size - Technical data analog outputs Number of outputs - Cable length, shielded - Rated load voltage -	Basic conversion time	-
Technical data analog outputs Number of outputs Cable length, shielded Rated load voltage	Noise suppression for frequency	-
Number of outputs - Cable length, shielded - Rated load voltage -	Initial data size	-
Number of outputs - Cable length, shielded - Rated load voltage -	Technical data analog outputs	
Cable length, shielded - Rated load voltage -		•
Rated load voltage -	·	-
		-
	<u> </u>	
	1.070100 polarity protocitors of rated load voltage	



Current consumption from load voltage L+ (without load)	-
Voltage output short-circuit protection	
Voltage outputs	
Min. load resistance (voltage range)	
Max. capacitive load (current range)	
Max. inductive load (current range)	
Output voltage ranges	
Operational limit of voltage ranges	
Basic error limit voltage ranges with SFU	
Destruction limit against external applied voltage	
Current outputs	
Max. in load resistance (current range)	
	-
Max. inductive load (current range) Typ. open circuit voltage current output	•
* * *	•
Output current ranges	-
Operational limit of current ranges	-
Radical error limit current ranges with SFU	-
Destruction limit against external applied voltage	-
Settling time for ohmic load	-
Settling time for capacitive load	-
Settling time for inductive load	-
Resolution in bit	-
Conversion time	·
Substitute value can be applied	·
Output data size	-
Technical data counters	
Number of counters	3
Counter width	32 Bit
Maximum input frequency	30 kHz
Maximum count frequency	30 kHz
Mode incremental encoder	yes
Mode pulse / direction	yes
Mode pulse	yes
Mode frequency counter	yes
Mode period measurement	yes
Gate input available	yes
Latch input available	yes
Reset input available	-
Counter output available	yes
Load and working memory	
Load memory, integrated	1024 KB
Load memory, maximum	1024 KB
Work memory, integrated	256 KB
Work memory, maximal	1024 KB
Memory divided in 50% program / 50% data	yes
Memory card slot	SD/MMC-Card with max. 2 GB
Hardware configuration	
Hardware configuration Racks, max.	4

Modules per rack, max.	8
Number of integrated DP master	1
Number of DP master via CP	4
Operable function modules	8
Operable communication modules PtP	8
Operable communication modules LAN	8
Status information, alarms, diagnostics	
	Via a
Status display	yes
Interrupts	yes
Process alarm	yes
Diagnostic interrupt	yes
Diagnostic functions	no
Diagnostics information read-out	possible
Supply voltage display	green LED
Group error display	red SF LED
Channel error display	red LED per group
Isolation	
Between channels	yes
Between channels of groups to	16
Between channels and backplane bus	yes
Between channels and power supply	-
Max. potential difference between circuits	DC 75 V/ AC 50 V
Max. potential difference between inputs (Ucm)	-
Max. potential difference between Mana and Mintern (Uiso)	-
Max. potential difference between inputs and Mana (Ucm)	-
Max. potential difference between inputs and Mintern (Uiso)	-
Max. potential difference between Mintern and outputs	-
Insulation tested with	DC 500 V
Command processing times	
Bit instructions, min.	0.02 μs
Word instruction, min.	0.02 μs
Double integer arithmetic, min.	0.02 μs
Floating-point arithmetic, min.	0.12 μs
Timers/Counters and their retentive characteristic	cs
Number of S7 counters	512
S7 counter remanence	adjustable 0 up to 256
S7 counter remanence adjustable	C0 C7
Number of S7 times	512
S7 times remanence	adjustable 0 up to 256
S7 times remanence adjustable	not retentive
Data range and retentive characteristic	
Number of flags	8192 Byte
Bit memories retentive characteristic adjustable	adjustable 0 up to 256
Bit memories retentive characteristic preset	MB0 MB15
Number of data blocks	4095
Max. data blocks size	64 KB
Max. local data size per execution level	510 Byte
() - () -	*

	IASIMA
Blocks	
Number of OBs	15
Number of FBs	2048
Number of FCs	2048
Maximum nesting depth per priority class	8
Maximum nesting depth additional within an error OB	4
Time	
Real-time clock buffered	yes
Clock buffered period (min.)	6 W
Accuracy (max. deviation per day)	10 s
Number of operating hours counter	8
Clock synchronization	yes
Synchronization via MPI	Master/Slave
Synchronization via Ethernet (NTP)	no
Address areas (I/O)	
Input I/O address area	1024 Byte
Output I/O address area	1024 Byte
Input process image maximal	128 Byte
Output process image maximal	128 Byte
Digital inputs	8064
Digital outputs	8064
Digital inputs central	1008
Digital outputs central	1008
Integrated digital inputs	16
Integrated digital outputs	16
Analog inputs	503
Analog outputs	503
Analog inputs, central	248
Analog outputs, central	248
Integrated analog inputs	0
Integrated analog outputs	0
Communication functions	
PG/OP channel	100
Global data communication	yes
	yes
Number of GD circuits, max. Size of GD packets, max.	4 22 Puto
	22 Byte
S7 basic communication	yes 70 Puto
S7 basic communication, user data per job	76 Byte
S7 communication	yes
S7 communication as server	yes
S7 communication as client	- 400 Puto
S7 communication, user data per job	160 Byte
Number of connections, max.	32
PWM data	
PWM channels	3
PWM time basis	0.1 ms / 1 ms
Period length	465535 / 165535 * time base
Minimum pulse width	00.5 * Period duration



Type of output Highside with 1.1kOhm pulldown

Type of output	Highside with 1.1kOhm pulldown
Functionality Sub-D interfaces	
Туре	X2
Type of interface	RS485
Connector	Sub-D, 9-pin, female
Electrically isolated	
MPI	yes
MP²I (MPI/RS232)	-
DP master	-
DP slave	-
Point-to-point interface	
5V DC Power supply	max. 90mA, non-isolated
24V DC Power supply	max. 100mA, non-isolated
Туре	X3
Type of interface	RS485
Connector	Sub-D, 9-pin, female
Electrically isolated	yes
MPI	-
MP²I (MPI/RS232)	-
DP master	yes
DP slave	yes
Point-to-point interface	yes
5V DC Power supply	max. 90mA, isolated
24V DC Power supply	max. 100mA, non-isolated
Functionality MPI	
Number of connections, max.	32
PG/OP channel	yes
Routing	yes
Global data communication	yes
S7 basic communication	yes
S7 communication	yes
S7 communication as server	yes
S7 communication as client	-
Transmission speed, min.	19.2 kbit/s
Transmission speed, max.	187.5 kbit/s
Functionality PROFIBUS master	
Number of connections, max.	32
PG/OP channel	yes
Routing	yes
S7 basic communication	yes
S7 communication	yes
S7 communication as server	yes
S7 communication as client	-
Activation/deactivation of DP slaves	Voc
	yes
Direct data exchange (slave-to-slave communication)	-
Direct data exchange (slave-to-slave communication) DPV1	•
	-

Transmission speed, max.	12 Mbit/s
Number of DP slaves, max.	32
Address range inputs, max.	1 KB
Address range outputs, max.	1 KB
User data inputs per slave, max.	244 Byte
User data outputs per slave, max.	244 Byte
	244 Dyle
Functionality PROFIBUS slave	
Number of connections, max.	32
PG/OP channel	yes
Routing	yes
S7 communication	yes
S7 communication as server	yes
S7 communication as client	-
Direct data exchange (slave-to-slave communication)	-
DPV1	yes
Transmission speed, min.	9.6 kbit/s
Transmission speed, max.	12 Mbit/s
Automatic detection of transmission speed	•
Transfer memory inputs, max.	244 Byte
Transfer memory outputs, max.	244 Byte
Address areas, max.	32
User data per address area, max.	32 Byte
Functionality RJ45 interfaces	
Туре	X5
Type of interface	Ethernet 10/100 MBit
Connector	RJ45
Electrically isolated	yes
Electrically isolated PG/OP channel	yes yes
	<u> </u>
PG/OP channel	yes
PG/OP channel Number of connections, max.	yes
PG/OP channel Number of connections, max. Productive connections	yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication	yes 4 -
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication	yes 4 - yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated	yes 4 - yes yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface	yes 4 - yes yes yes -
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface	yes 4 - yes yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface	yes 4 - yes yes yes yes yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector	yes 4 - yes yes yes yes yes Sub-D, 9-pin, female
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max.	yes 4 - yes yes yes yes Sub-D, 9-pin, female 150 bit/s
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max.	yes 4 - yes yes yes yes yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol	yes 4 - yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol	yes 4 - yes yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol	yes 4 - yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol STX/ETX protocol 3964(R) protocol	yes 4 - yes yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol STX/ETX protocol RK512 protocol	yes 4 - yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m yes yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol STX/ETX protocol RK512 protocol USS master protocol	yes 4 - yes yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m yes yes yes yes
PG/OP channel Number of connections, max. Productive connections Point-to-point communication PtP communication Interface isolated RS232 interface RS422 interface RS485 interface Connector Transmission speed, min. Transmission speed, max. Cable length, max. Point-to-point protocol ASCII protocol STX/ETX protocol RK512 protocol	yes 4 - yes yes yes - yes Sub-D, 9-pin, female 150 bit/s 115.5 kbit/s 500 m yes yes yes



Special protocols

Housing	
Material	PPE
Mounting	Rail System 300
Mechanical data	
Dimensions (WxHxD)	80 mm x 125 mm x 120 mm
Net weight	420 g
Weight including accessories	
Gross weight	
Environmental conditions	
Operating temperature	0 °C to 60 °C
Storage temperature	-25 °C to 70 °C
Certifications	
UL certification	yes
KC certification	yes